


Pulse Transformer

Turns Ratio (± 2%)	1.3 : 1.0
----------------------	-----------

Parameter	Min.	Max.	Units
*Open Circuit Inductance Oscillation Voltage = 1V Oscillation Frequency = 100 KHz	1.0		mH
Interwinding Capacitance (C_{ww}) Oscillation Frequency = 100 KHz		15	pF
Primary DC Resistance		1.7	ohms
Secondary DC Resistance		1.0	ohms
Isolation (HI-POT)	1000		V_{RMS}


Schematic Diagram



Pin3 is Shield

* Tested on Primary Pins 1 & 2

Physical Dimensions in inches (mm)



RHOMBUS P/N: T-802	
CUST P/N:	NAME:
DATE: 5/14/96	SHEET: 1 of 1